Satisfy Professional's Needs



## **Trakita** Cordless Blower DUB184

# Powerful & Lightweight











# **Powerful Cordless Blower Powered by One 18V battery**



Installing the flat nozzle or extension nozzle (option)

Flat nozzle



**Extension nozzle** 

**Adapter pipe** 











High power **Brushless Motor** 







For use in outdoor applications or harsh environments, protection from dust and dripping water is enhanced.









On a single full battery charge with max air setting

6.0Ah BL1860B

3

4

5

8

10

12

#### Hole on the bottom of housing for hanging the machine







#### **Accessories**

Flat nozzle Part No. 197889-6



Extension nozzle Part No. 197888-8







Attach the flat nozzle or extension nozzle to the adapter pipe, and then turn it to lock it into place. Shoulder strap Part No. 166094-6











<b>Cordless Blowe</b>	Cord	less B	lowe
-----------------------	------	--------	------

鄼 Variable Speed Constant Speed

**DUB184** 

Max Air Volume Max Air Velocity No Load Speed (RPM) Continuous Use (min.) Sound Pressure Level Sound Power Level Vibration Level Vibration Level Dimensions(L x W x H)

13.0 m<sup>3</sup>/min (459 CFM) 52.1 m/s (116 MPH) 0 - 18,000 w/ BL1860B: 12, w/ BL1850B: 10 86.6 dB(A) 93.5 dB(A) 2.5 m/s<sup>2</sup> or less w/ BL1815N / BL1820B: 810x160x285 mm (32\*x6-5/16\*x11-1/4") w/ BL1830B / BL1840B / BL1850B / BL1860B: 825x160x285 mm (32-1/2\*x6-5/16\*x11-1/4") 2.5 - 3.0 kg (5.4 - 6.7 lbs.)

Net weight

Standard Equipment : Hex Wrench

The weight may differ depending on the attachment(s), including the battery cartridge. The lightest and heaviest combination, according to EPTA-Procedure 01/2014, are shown in the table. Items of standard equipment and specifications may vary by country or area.

### Makita Corporation

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan